

SO-SFP28-32GFC-SD

SFP28, 32G FC, 25GbE, 850nm, MM, DDM, 7dB, 100m

OVERVIEW

The SO-SFP28-32GFC-SD is an 850nm SFP28 transceiver for MultiMode (MM) fiber, supporting both 32G Fiber Channel (FC) as well as 25G Ethernet services. The optical performance provides a bridgeable distance of up to 100 m for 32G FC when using an OM4 grade MM fiber.

The transceiver has no minimum distance (i.e. no minimum attenuation) which is ideal for intra-office connections since extra attenuators need not be considered.

This transceiver provides digital diagnostic functions via a 2-wire serial interface as defined by the SFF-8472 specification.

As stipulated by the 32G FC and 25G Ethernet standards, Forward Error Correction (FEC) is required to be implemented by the host to ensure reliable system operation. The optical parameters below will provide a bit error ratio (BER) of 1×10^{-6} for 32G FC and 5×10^{-5} for 25GbE. FEC will provide the required quality for secure service.

TECHNICAL DATA

Parameter	Value
Technology	Grey SFP28
Transmission media	MM (2x LC)
Typical reach	100m @ OM4, 70m @ OM3
Nominal wavelength	850nm
Bit rate support	28.05Gbps (FC) 25.78Gbps (Eth)
Protocol support	32G FC 25GE
Power budget	0 – 7.0dB for 32G FC 0-1.9dB for 25GE
Power consumption	< 1.0W
Operating temperature	-0°C to +70°C
Storage temperature	-40°C to +85°C

Parameter	Value
Transmitter data:	
Output power 32G FC	Min: -1.4dBm ¹⁾
	Max: +2.0dBm ¹⁾
25GE	Min: -8.4dBm ¹⁾
	Max: +2.4dBm ¹⁾
Transmit wavelength	840nm – 860nm
Receiver data:	
Minimum input power 32G FC	-8.4dBm ^{1) 2)}
	-10.3dBm ^{1) 2)}
25GE	-10.3dBm ^{1) 2)}
Overload (max power)	+2.4dBm ^{1) 2)}
Wavelength range	840nm – 860nm
LOS Assert	Min -20dBm
LOS De-assert	Max -12dBm
LOS Hysteresis	Min 0.5dB
DDM	Yes
MSA compliance	SFF-8402, -8472

¹⁾ Average power.

²⁾ @ BER 1×10^{-6} , back-to-back.

Safety/regulatory compliance:

TUV/UL/FDA (contact Smartoptics for latest certification information)

RoHS compliance

Subject to change without notice.

For more information visit smartoptics.com.

smartoptics

ORDERING INFORMATION

Ordering code	Description
SO-SFP28-32GFC-SD	SFP28, 32G FC, 25G Ethernet, MM, 850nm, 100m@OM4, 7dB, LC

GENERAL DEFINITIONS

Parameter	Description
Technology	Grey; Transceiver type for non-WDM applications. Electrical or optical. CWDM; Transceiver type for CWDM applications using G.694.2 channel grid. DWDM; Transceiver type for DWDM applications using G.694.1 channel grid. BiDi; Transceiver pair using two different wavelength channels operating on a single-fiber. DAC: Direct Attach Cable. Electrical cable with attached connectors. AOC: Active Optical Cable. Optical cable with attached connectors.
Transmission Media	Type of fiber, e.g. Multimode (MM) or Singlemode (SM). Number of and connector type within brackets (e.g. 2x LC, 1x MPO).
Typical reach	Nominal distance performance based on typical fiber dispersion, fiber loss and power budget properties, i.e. w/o dispersion compensation and optical amplification. Actual distance is dependent on actual optical path loss and dispersion properties.
Bit rate range	Supported bit rate range in Gigabit or Megabit per second (Gbps or Mbps).
Protocols	Protocols within supported bit rate range.
Nominal wavelength	Typical wavelength(s) from transmitter.
Interface standards	Referenced interface standards or MSA's, e.g. IEEE 802.3 standard for 10GbE services or 100G 4WDM-10 etc.
Power budget	Min and max power budget between Transmitter and Receiver w/o optical path penalties.
Dispersion tolerance/penalty	Maximum amount of tolerated dispersion and required reduction of power budget to maintain stipulated Bit Error Rate (BER) and at a given bit rate.
Temperature range	Max operating case temperature range. Standard temperature range (C-temp): 0°C to +70°C (32°F to +158°F) Extended temperature range (E-temp): typically -20°C to +75°C (-4°F to +167°F) Industrial temperature range (I-temp): -40°C to +85°C (-40°F to +185°F)
Power consumption	Worst case power consumption. Will vary over temperature.
Transmitter Output power	Average output power. Provided in min and max values.
Receiver minimum input power	Minimum average input power at specified BER, normally $1E^{-12}$. Note that some protocols require FEC to achieve sufficient BER.
Receiver max input power	Maximum average input power giving a BER, normally $1E^{-12}$.
DDM	Digital Diagnostic Monitoring functionality as defined in e.g. SFF-8472 MSA.

Smartoptics makes no warranties or representations, expressed or implied, of any kind relative to the information or any portion thereof contained in this document or its adaptation or use, and assumes no responsibility or liability of any kind, including, but not limited to, indirect, special, consequential or incidental damages, for any errors or inaccuracies contained in the information or arising from the adaptation or use of the information or any portion thereof. The information in this document is subject to change without notice.