

SO-QSFP56-2C-2

QSFP56 200G-FR4 Ethernet, 1271nm/1311nm/1311nm/1331nm, 2km, 4.8dB, LC

OVERVIEW

The SO-QSFP56-2C-2 is a QSFP56 form-factor transceiver for 200Gbps Ethernet applications. It is intended for use in data center interconnect between switches, routers, storage equipment etc. for optical distances up to 2km over a SingleMode (SM) fiber cable.

The module has 4 independent electrical input/output channels operating at 26.5625Gbd per channel. This transceiver uses four PAM4 modulated lanes operating at the ITU G.694.2 CWDM grid. The transceiver requires that the host system uses Forward Error Correction (FEC).

The electrical interface is compliant with the 200GAUI-4 interface as defined by IEEE 802.3bs.

Digital diagnostics functions are available via an I²C interface, as specified by the QSFP56 MSA using CMIS4.0.

TECHNICAL DATA

Parameter	Value
Technology	Grey QSFP56
Transmission media	SM (2x LC)
Typical reach	2km
Nominal wavelengths	1271nm
	1291nm
	1311nm
	1331nm
Interface standards	IEEE 200GBASE-FR4
Bit rate support	212.5Gbps ¹⁾
	26.5625Gbd (PAM4) ²⁾
Protocol support	200GbE
Power budget	0 –4.8dB
Power consumption	< 5.5W (typical <4.5W)
Operating temperature	0°C to +70°C
Storage temperature	-40°C to +85°C

¹⁾ Aggregated line rate 200GbE

²⁾ Line rate per lane

³⁾ Specified at BER 2x10⁻⁴

Parameter	Value
Transmitter data:	
Total output power	Max: +10.7dBm
Output power, per lane	Min: 0dBm
	Max: +4.7dBm
Transmit wavelengths	1264.5 – 1277.5nm
	1284.5 – 1297.5nm
	1304.5 – 1317.5nm
	1324.5 - 1317.5nm
Receiver data:	
Minimum input power per lane	-4.8dBm ³⁾
Overload (max power) per lane	+4.7dBm ³⁾
Wavelength range	1264.5 – 1277.5nm
	1284.5 – 1297.5nm
	1304.5 – 1317.5nm
	1324.5 - 1317.5nm
LOS Assert	Min 17dBm
LOS De-Assert	Max -12dBm
LOS Hysteresis	Min 0.5dBm
DDM	Yes
MSA compliance	QSFP56 MSA, SFF8636

Safety/regulatory compliance:

TUV/UL/FDA (contact Smartoptics for latest certification information)

RoHS compliance

Subject to change without notice.

For more information visit smartoptics.com.

smartoptics

ORDERING INFORMATION

Ordering number	Description
SO-QSFP56-2C-2	QSFP56 200G-FR4 Ethernet, 1271nm/1311nm/1311nm/1331nm, 2km, 4.8dB, CMIS4.0, LC

GENERAL DEFINITIONS

Parameter	Description
Technology	Grey; Transceiver type for non-WDM applications. Electrical or optical. CWDM; Transceiver type for CWDM applications using G.694.2 channel grid. DWDM; Transceiver type for DWDM applications using G.694.1 channel grid. BiDi; Transceiver pair using two different wavelength channels operating on a single-fiber. DAC: Direct Attach Cable. Electrical cable with attached connectors. AOC: Active Optical Cable. Optical cable with attached connectors.
Transmission Media	Type of fiber, e.g. Multimode (MM) or Singlemode (SM). Number of and connector type within brackets (e.g. 2x LC, 1x MPO).
Typical reach	Nominal distance performance based on typical fiber dispersion, fiber loss and power budget properties, i.e. w/o dispersion compensation and optical amplification. Actual distance is dependent on actual optical path loss and dispersion properties.
Bit rate range	Supported bit rate range in Gigabit or Megabit per second (Gbps or Mbps).
Protocols	Protocols within supported bit rate range.
Nominal wavelength	Typical wavelength(s) from transmitter.
Interface standards	Referenced interface standards or MSA's, e.g. IEEE 802.3 standard for 10GbE services or 100G 4WDM-10 etc.
Power budget	Min and max power budget between Transmitter and Receiver w/o optical path penalties.
Dispersion tolerance/penalty	Maximum amount of tolerated dispersion and required reduction of power budget to maintain stipulated Bit Error Rate (BER) and at a given bit rate.
Temperature range	Max operating case temperature range. Standard temperature range (C-temp): 0°C to +70°C (32°F to +158°F) Extended temperature range (E-temp): typically -20°C to +75°C (-4°F to +167°F) Industrial temperature range (I-temp): -40°C to +85°C (-40°F to +185°F)
Power consumption	Worst case power consumption. Will vary over temperature.
Transmitter Output power	Average output power. Provided in min and max values.
Receiver minimum input power	Minimum average input power at specified BER, normally $1E^{-12}$. Note that some protocols require FEC to achieve sufficient BER.
Receiver max input power	Maximum average input power giving a BER, normally $1E^{-12}$.
DDM	Digital Diagnostic Monitoring functionality as defined in e.g. SFF-8472 MSA.

Smartoptics makes no warranties or representations, expressed or implied, of any kind relative to the information or any portion thereof contained in this document or its adaptation or use, and assumes no responsibility or liability of any kind, including, but not limited to, indirect, special, consequential or incidental damages, for any errors or inaccuracies contained in the information or arising from the adaptation or use of the information or any portion thereof. The information in this document is subject to change without notice.