

SO-SFP-1000BASE-L40D & L40D-I

SFP, 1.0625/1.25Gbps, 1310nm, SM, DDM, 22dB, 40km, C-temp & I-temp

OVERVIEW

SO-SFP-1000BASE-L40D is a 1310nm SFP transceiver for SingleMode fiber for Gigabit Ethernet (GbE) and 1G Fiber Channel (1G FC) services. The optical performance provides a bridgeable distance of up to 40 km.

This transceiver provides digital diagnostic functions via a 2-wire serial interface as defined by the SFF-8472 specification. The transceiver is available in two temperature range options, one being the Industrial temperature range (I-temp): -40°C to 85°C (-40°F to 185°F).

TECHNICAL DATA

Parameter	Value
Technology	Grey SFP
Transmission media	SM (2x LC)
Typical reach	40km
Nominal wavelength Tx/Rx	1x 1310nm
Bit rate support	1.0625Gbps / 1.25Gbps
Protocol support	GbE 1G FC
Power budget	6 – 22dB
Power consumption	< 1.0W
Operating temperature	0°C to +70°C -40°C to +85°C (-I)
Storage temperature	-40°C to +85°C

Parameter	Value
Transmitter data:	
Output power	Min: -2.0dBm ¹⁾ Max: +3.0dBm ¹⁾
Transmit wavelength	1260 – 1360nm
Receiver data:	
Minimum input power	-24.0dBm ^{1) 2)}
Overload (max power)	-3.0dBm ^{1) 2)}
Wavelength range	1260 – 1600nm
LOS Assert	Min -38dBm
LOS De-assert	Max -25dBm
LOS Hysteresis	Min 0.5dB
DDM	Yes
MSA compliance	SFF-8431, -8432, -8472

¹⁾ Average power.

²⁾ @ 1.25Gbps, BER ≤ 1x10⁻¹², PRBS 2⁷-1, back-to-back.

Safety/regulatory compliance:

TUV/UL/FDA (contact Smartoptics for latest certification information)

RoHS compliance

ORDERING INFORMATION

Ordering code	Description
SO-SFP-1000Base-L40D	SFP, 1G Ethernet, 1G FC, SM 1310nm, 40km, 22dB, LC
SO-SFP-1000Base-L40D-I	SFP, 1G Ethernet, 1G FC, SM 1310nm, 40km, 22dB, I-temp, LC

GENERAL DEFINITIONS

Parameter	Description
Technology	Grey; Transceiver type for non-WDM applications. Electrical or optical. CWDM; Transceiver type for CWDM applications using G.694.2 channel grid. DWDM; Transceiver type for DWDM applications using G.694.1 channel grid. BiDi; Transceiver pair using two different wavelength channels operating on a single-fiber. DAC: Direct Attach Cable. Electrical cable with attached connectors. AOC: Active Optical Cable. Optical cable with attached connectors.
Transmission Media	Type of fiber, e.g. Multimode (MM) or Singlemode (SM). Number of and connector type within brackets (e.g. 2x LC, 1x MPO).
Typical reach	Nominal distance performance based on typical fiber dispersion, fiber loss and power budget properties, i.e. w/o dispersion compensation and optical amplification. Actual distance is dependent on actual optical path loss and dispersion properties.
Bit rate range	Supported bit rate range in Gigabit or Megabit per second (Gbps or Mbps).
Protocols	Protocols within supported bit rate range.
Nominal wavelength	Typical wavelength(s) from transmitter.
Interface standards	Referenced interface standards or MSA's, e.g. IEEE 802.3 standard for 10GbE services or 100G 4WDM-10 etc.
Power budget	Min and max power budget between Transmitter and Receiver w/o optical path penalties.
Dispersion tolerance/penalty	Maximum amount of tolerated dispersion and required reduction of power budget to maintain stipulated Bit Error Rate (BER) and at a given bit rate.
Temperature range	Max operating case temperature range. Standard temperature range (C-temp): 0°C to +70°C (32°F to +158°F) Extended temperature range (E-temp): typically -20°C to +75°C (-4°F to +167°F) Industrial temperature range (I-temp): -40°C to +85°C (-40°F to +185°F)
Power consumption	Worst case power consumption. Will vary over temperature.
Transmitter Output power	Average output power. Provided in min and max values.
Receiver minimum input power	Minimum average input power at specified BER, normally $1E^{-12}$. Note that some protocols require FEC to achieve sufficient BER.
Receiver max input power	Maximum average input power giving a BER, normally $1E^{-12}$.
DDM	Digital Diagnostic Monitoring functionality as defined in e.g. SFF-8472 MSA.

Smartoptics makes no warranties or representations, expressed or implied, of any kind relative to the information or any portion thereof contained in this document or its adaptation or use, and assumes no responsibility or liability of any kind, including, but not limited to, indirect, special, consequential or incidental damages, for any errors or inaccuracies contained in the information or arising from the adaptation or use of the information or any portion thereof. The information in this document is subject to change without notice.