

SFP56 50G-SR

SFP56, 50G, 850nm, MM, DDM, 2.0dB, 70m@OM3, 100m@OM4

TS5001-M85C-SO

The TS5001-M85C-SO is an SFP+ form-factor transceiver for 50Gbps Ethernet applications. Since the transmission rate can reach up to 56Gbps, the engineering and industry name is SFP56. It is intended for use in inter- and intra-connect applications within data centers between switches, routers, storage equipment etc. The optical performance is in accordance with the IEEE 50GBASE-SR standard, i.e. for optical distances up to 100m over a MultiMode (MM) OM4-grade fiber.

TS5001-M85C-SO uses a single 850nm channel @ 53.125 Gbps to transport a 50G Ethernet signal. Digital diagnostics functions are available via an I2C interface, as specified by the MSA.

As stipulated by the 50G Ethernet standards, Forward Error Correction (FEC) is required to be implemented by the host to ensure reliable system operation. The optical parameters below will provide a bit error ratio (BER) of 2.4×10^{-4} for 50G Ethernet. FEC will provide the required quality for secure service.

TECHNICAL DATA

Parameter	Value
Technology	Grey SFP56
Transmission media	MM (2x LC)
Typical reach	70m @ OM3, 100m @ OM4
Nominal wavelength	1x 850nm
Interface standards	50GBASE-SR
Bit rate support	53.125 Gbps
Protocol support	50GbE
Power budget	0 – 2.0dB
Power consumption	< 1.5W
Operating temperature	0°C to +70°C
Storage temperature	-40°C to +85°C

¹⁾ Average receive power (min) is informative and not the principal indicator of signal strength. A received power below this value cannot be compliant; however, a value above this does not ensure compliance.

²⁾ at 53.125 Gbps (50GE) and BER 2.4×10^{-4}

Parameter	Value
Transmitter data:	
Output power, average	Min: -6.5dBm ¹⁾ Max: +4.0Bm
Output power, OMA	Min: -4.5dBm Max: +3.0dBm
Transmit wavelength	840 – 860nm
Receiver data:	
Receiver sensitivity, OMA	-6.5dBm ²⁾
Minimum input power, average	-8.4dBm ¹⁾
Overload, average (max power)	+4.0dBm ²⁾
Wavelength range	840 – 860nm
LOS Assert	Min -17dBm
LOS De-assert	Max -11dBm
LOS Hysteresis	Min 0.5dB

Safety/regulatory compliance:

TUV/UL/FDA (contact Smartoptics for latest certification information)

RoHS compliance

ORDERING INFORMATION

Ordering number	Description
TS5001-M85C-SO	SFP56, 50G, 850nm, MM, DDM, 2.0dB, 70m@OM3, 100m@OM4

GENERAL DEFINITIONS

Parameter	Description
Technology	Grey; Transceiver type for non-WDM applications. Electrical or optical. CWDM; Transceiver type for CWDM applications using G.694.2 channel grid. DWDM; Transceiver type for DWDM applications using G.694.1 channel grid. BiDi; Transceiver pair using two different wavelength channels operating on a single-fiber. DAC: Direct Attach Cable. Electrical cable with attached connectors. AOC: Active Optical Cable. Optical cable with attached connectors.
Transmission Media	Type of fiber, e.g. Multimode (MM) or Singlemode (SM). Number of and connector type within brackets (e.g. 2x LC, 1x MPO).
Typical reach	Nominal distance performance based on typical fiber dispersion, fiber loss and power budget properties, i.e. w/o dispersion compensation and optical amplification. Actual distance is dependent on actual optical path loss and dispersion properties.
Bit rate range	Supported bit rate range in Gigabit or Megabit per second (Gbps or Mbps).
Protocols	Protocols within supported bit rate range.
Nominal wavelength	Typical wavelength(s) from transmitter.
Interface standards	Referenced interface standards or MSA's, e.g. IEEE 802.3 standard for 10GbE services or 100G 4WDM-10 etc.
Power budget	Min and max power budget between Transmitter and Receiver w/o optical path penalties.
Dispersion tolerance/penalty	Maximum amount of tolerated dispersion and required reduction of power budget to maintain stipulated Bit Error Rate (BER) and at a given bit rate.
Temperature range	Max operating case temperature range. Standard temperature range (C-temp): 0°C to +70°C (32°F to +158°F) Extended temperature range (E-temp): typically -20°C to +75°C (-4°F to +167°F) Industrial temperature range (I-temp): -40°C to +85°C (-40°F to +185°F)
Power consumption	Worst case power consumption. Will vary over temperature.
Transmitter Output power	Average output power. Provided in min and max values.
Receiver minimum input power	Minimum average input power at specified BER, normally $1E^{-12}$. Note that some protocols require FEC to achieve sufficient BER.
Receiver max input power	Maximum average input power giving a BER, normally $1E^{-12}$.
Optical Modulation Amplitude, OMA	Optical Modulation Amplitude is a parameter that, in certain standards, specifies the output power and as receiver sensitivity. To measure the OMA, a oscilloscope with a baud rate corresponding to the transceiver is required. Thus, this parameter cannot be measured using an ordinary optical power meter.
DDM	Digital Diagnostic Monitoring functionality as defined in e.g. SFF-8472 MSA.

Smartoptics makes no warranties or representations, expressed or implied, of any kind relative to the information or any portion thereof contained in this document or its adaptation or use, and assumes no responsibility or liability of any kind, including, but not limited to, indirect, special, consequential or incidental damages, for any errors or inaccuracies contained in the information or arising from the adaptation or use of the information or any portion thereof. The information in this document is subject to change without notice.